SOFTWARE COMPENSATION OF GYROSCOPIC SENSOR DRIFT IN DIRECTIONAL DRILLING NAVIGATION SYSTEMS USING NON-LINEAR EXTENDED KALMAN FILTERING AND ZERO-VELOCITY UPDATE ALGORITHMIC FRAMEWORKS

Ashurov Abror Uchkunovich
Chief Geophysicist, "Central Geological and Geophysical Expedition" JSC "Uzbekgeologorazvedka", Tashkent, Uzbekistan.
e-mail: abrorashurov1986@gmail.com

Abstract. *This scientific paper evaluates the software and algorithmic methods for mitigating sensor errors inherent in inertial navigation systems utilized for the high-precision determination and real-time operational control of directional drilling trajectories. To dynamically minimize the cumulative systematic drifts of gyroscopic sensors under conditions characterized by severe magnetic anomalies, steel casings, and highly mineralized environments, an integrated mathematical model combining a 15-state non-linear Extended Kalman Filter (EKF) and a Zero-Velocity Update (ZUPT) calibration algorithm triggered during brief stationary intervals was developed and verified via computer-aided simulation frameworks.*

Keywords: *Inertial navigation system, gyroscopic inclinometer, Extended Kalman Filter, Zero-Velocity Update, sensor drift, azimuth, inclination angle, drift compensation, digital signal processing.*

Introduction and problem statement

In modern geological exploration, mining, and oil and gas industries, precise spatial control of the borehole trajectory serves as the strategic cornerstone for efficient reservoir development. Practical field deployment demonstrates that under actual geological conditions, a borehole trajectory is rarely perfectly vertical; instead, it deviates spontaneously under the influence of rock hardness and complex tectonic formations. Conventional magnetic inclinometers, which are widely deployed today, introduce gross measurement errors due to electromagnetic noise generated by steel casing pipes, ferromagnetic/magnetite mineral strata, and the metallic drill string itself.

In deep boreholes—for example, at a depth of 1000 meters—such cumulative errors can cause the borehole bottom to deviate by more than 50–100 meters from its planned path, causing the drill bit to completely miss the productive formation matrix. The only viable solution to this critical issue lies in the implementation of gyroscopic and inertial navigation principles, which function completely independently of external magnetic environments. However, due to the inherent physical characteristics of

navigation-grade gyroscopic sensors, they suffer from cumulative systematic sensor drift over time. In long-term measurements, this drift causes coordinate determination errors to amplify exponentially relative to the square of time (t^2).

Research methodology and mathematical modeling

Within the scope of this research, a 15-state Extended Kalman Filter (EKF) architecture was designed to estimate and compensate for sensor errors in real time as the gyroscopic probe moves through the borehole. The system state vector (X) incorporates the following multi-axial parameters: three-axis position errors, three-axis velocity errors, three-axis orientation (inclination and azimuth) angle errors, three-axis accelerometer biases, and three-axis systematic gyroscopic drift rates ($0.003^\circ/\text{hr}$ to $0.1^\circ/\text{hr}$). Since the foundational system equations exhibit non-linear characteristics, linearization procedures are executed at each discrete time step using Taylor series expansion and Jacobian matrices.

The filter operational pipeline functions within a two-stage recursive cycle:

1. **Prediction Phase:** High-frequency raw data sampled from the inertial measurement unit (IMU) every 10 milliseconds are passed through kinematic integration equations to continuously project the subsequent coordinates and orientation angles of the device. Concurrently, the system uncertainty boundary and the error covariance matrix (P) expand.

2. **Correction Phase:** Exploiting the unique operational characteristics of the drilling sequence—such as drill pipe connections or operator standby intervals—the Zero-Velocity Update (ZUPT) algorithm is activated when the absolute physical velocity of the probe drops to zero. Any artificial velocity indicated by the inertial system during this stationary window is flagged as a raw measurement residual. Using the computed Kalman Gain, the internal systematic gyroscopic drift is mathematically isolated through a closed-loop feedback network and updated in the system registry, effectively resetting the drift accumulation to zero.

Conclusion

The successful algorithmic integration of theoretical research and digital signal processing has yielded a robust mathematical and software foundation for a localized, high-precision navigation system. This framework operates entirely independently of external electromagnetic interference, bypassing the historical constraints of static point-by-point measurements to provide a continuous, high-fidelity spatial trajectory profile sampled at ultra-fine 10-centimeter spatial intervals.

REFERENCES

1. **Bar-Shalom, Y., Li, X. R., & Kirubarajan, T.** (2001). *Estimation with Applications to Tracking and Navigation: Theory Algorithms and Software*. Hoboken: John Wiley & Sons. (Kalman filtrlarining chiziqli bo‘lmagan tizimlardagi matematik asoslari bo‘yicha fundamental qo‘llanma).
2. **Chatfield, A. B.** (1997). *Fundamentals of High Accuracy Inertial Navigation*. Reston: American Institute of Aeronautics and Astronautics (AIAA). (Inersial navigatsiyada sensorlar og‘ishi (dreyf) va koordinata xatoligining vaqt kvadratiga bog‘liqligi matematik tahlili).
3. **Grewal, M. S., Weill, L. R., & Andrews, A. P.** (2020). *Global Positioning Systems, Inertial Navigation, and Integration (4th Edition)*. Hoboken: John Wiley & Sons. (15 ta holatli Extended Kalman Filter (EKF) va quduq navigatsiyasi tizimlarining sintezi).
4. **Groves, P. D.** (2013). *Principles of GNSS, Inertial, and Multisensor Integrated Navigation Systems (2nd Edition)*. Boston: Artech House. (Nollashgan tezlikni yangilash (ZUPT) algoritmlari va IMU datchiklarini statsionar holatda dasturiy kalibrlash qonuniyatlari).
5. **Honeywell, Inc.** (2013). *3-Axis Digital Compass IC HMC5883L Datasheet*. Plymouth: Honeywell Microelectronics & Memory Products.
6. **Savage, P. G.** (1998). *Strapdown Inertial Navigation Integration Algorithm Design*. *Journal of Guidance, Control, and Dynamics*, 21(1), 19-28. (Har 10 millisekundda olinadigan yuqori chastotali xom ma’lumotlarni integrallash algoritmlari).
7. **Titterton, D., & Weston, J.** (2004). *Strapdown Inertial Navigation Technology (2nd Edition)*. London: Institution of Electrical Engineers. (Giroskopik sensorlarning dreyf ko‘rsatkichlari va Yakobian matritsalari yordamida chiziqlilashtirish amallari).